



# EJ-501TM Push to talk

## UHF Handheld Microphone

### Features

- UHF 16~96-ch handheld microphone
- UHF band 520-865MHz.
- 16/96 channels available (depending on frequency band).
- Talk/Mute button.
- Hi/Low power switch.
- Built-in condenser mike.
- LCD display.
- Battery meter.
- Aux/Mic input.

### Technical specifications

Microphone	Condenser capsule
Frequency range	520 ~ 865 MHz (country dependent)
Adjustable channels	16 or 96 channels, by frequency range
Antenna	built-in
RF output	10 mW
AF controls	Talk / Mute button
Battery	2 AA 1.2 V (Ni-MH. 1600 mAh), 2 AA 1.5V (Alkaline)
Battery life Ni-MH. rechargeable	13 hours typical
Battery life Alkaline disposable	20 hours typical
Dimension (Dia x L)	37 x200 (mm)
Weight	140 g (with batteries)

For additional information, please refer to User Guide/Installation Guide and CE Certificate. Download from [www.univox.eu](http://www.univox.eu).



Bo Edin AB  
Sweden and International Sales

+46 (0)8 767 18 18  
[info@edin.se](mailto:info@edin.se)  
[www.univox.eu](http://www.univox.eu)

UnivoxAudio Ltd.  
UK Sales

+44 (0)1707 339216  
[writeto@univoxaudio.co.uk](mailto:writeto@univoxaudio.co.uk)  
[www.univoxaudio.co.uk](http://www.univoxaudio.co.uk)

